

PORTABLE GAS DETECTOR

H2000



Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81

Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пenza (8412)22-31-16

Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13

Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93



PORTABLE 4 GAS DETECTOR H2000

H2000 is portable 4 gas detector for LEL, O2, H2S, CO, gas type is customizable. Based on advanced sensor technology and IP66, it makes you more confident in harsh environments. You can check the alarm record on the detector.



Sound, Light,
Vibration



dib Design
IP66



Rechargeable
Type-C USB

PC+ABS+Rubber
Drop Protection



Advanced Sensors
Fast Response



Compact Design
Easy to Go



Specifications

Description	H2000
Function	
gas detected	CH4、O2、CO、toxic gas
measure range	see QUICK-SELECTION-TABLE
response time*	T90≤30/60/180S
accuracy*	≤±5%FS
repeatability*	≤2%FS
sampling method	diffusion
Electric	
battery	rechargeable Li-battery 1800mAh, nominal voltage 3.7V
continuous operation	≥9h
charging time	4-6h
Alarm	
alarm method	sound,LED light,vibration
sound intensity	≥90dB
Display and Operation	
display	TFT Color display screen
button	3 (UP、DOWN、ENTER)
Environment	
ingress protection	IP66
operating temperature*	-20℃~60℃
operating humidity	10~95%RH non-condensing
operating pressure	80-120kPa
Structure	
body material	PC+ABS
weight	200g
dimensions	66X127X46mm
Certificates	
EX	Exdib II CT4 Gb

Note:* refers to there's some difference vary from different gas, please contact the manufacturer for details.

QUICK SELECTION TABLE -- GAS DETECTED

NO.	Gas	Measure range	Resolution
1	O2	0-25%VOL	0.1%VOL
2	CO	0-1000ppm	1ppm
3	H2S	0-100ppm	1ppm
4	SO2	0-20ppm	0.1ppm
5	H2	0-1000ppm	1ppm
6	CL2	0-10ppm	0.1ppm
7	NH3	0-100ppm	1ppm
8	HCL	0-30ppm	0.1ppm
9	NO	0-250ppm	1ppm
10	NO2	0-20ppm	0.1ppm
11	ETO	0-20ppm	0.1ppm
12	CH4	0 ~100%LEL	1%LEL

Note: 1, Any gas or measure range that not mentioned above, just contact AIYI Technologies for further information; 2, 1μmol/mol=1ppm

Архангельск (8182)63-90-72
Астана (7172)727-132
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06

Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81

Киргизия (996)312-96-26-47

Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16

Россия (495)268-04-70

Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13

Казахстан (772)734-952-31

Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93

<https://aiyi.nt-rt.ru/> || aya@nt-rt.ru